



#### Various access

Be-Tech i8A1FMT has three access solutions, Fingerprint, RF Card key or PIN code for your convenience.



### **One-touch Fingerprint Verification**

One-touch Fingerprint verification technology has been applied to conveniently read a fingerprint in one shot.



# **Operation status notification**

Whenever any operation is made, the LED indicator informs you what is happening through different colors and signs.



### **Scramble code**

You can enter random numbers prior to the right code when there is a chance of exposing it to others.



### **Automatic locking**

Door lock will be locked automatically after opening door a few seconds. (Manual operation is also available)



### Missing key invalidation

Once you lose your key, it has no validation as long as you re-register rest of your keys.



## **Anti-panic exit system**

For convenience and in case of emergency, it allows you to open the door by simply turning its handle from inside.



# Alarm (Incorrect Fingerprint, RF Card or PIN code)

Alarm will be on and last for 60 seconds if anyone attempts to open the lock with incorrect Fingerprint, RF Card or PIN code for 5 times.



## Low battery warning signal

A continuous "beep" sound during door access will alert you to replace batteries.



### **Invisible keypad**

Keypad number can be seen only when you touch the screen with your palm.



### Mechanical key override

For emergency, it can also be unlocked with a mechanical key.



i8A1FMT

Convenient

Model





Reliable

Safe



# **Specification**

openited to it		
Parts	Specifications	Remarks
Front(Front Body)	$77(W)\times354(H)\times83(D)$ (with door handle)mm, Zinc Alloy	Temperature: Workable -20°C~60°C Humidity: Workable 20%~93% ± 2RH
Back(Back Body)	77(W) $\times$ 354(H) $\times$ 86(D)(with door handle)mm, Zinc Alloy	
Door Thickness	Applicable Range 40-80mm	
Lock case	Stainless Steel	
Fingerprint	Up to 91 Groups	
Card Keys	Up to 44 keys(1Master key & 40 User keys & 3 Staff keys)	
User Codes	Up to 3 Groups, 6~12Digits(000000~0000000000)	
Battery	4X1.5V AA alkaline batteries(Operating voltage: 4.3~6.5V)	Last up to 12 months(10 times used a day)

## Contact us:

Smart Your Life



**Guangdong Be-Tech Security Systems Limited** 

No.17, KeYuan 3 Road, Ronggui Shunde High-Tech Zone, Foshan, Guangdong 528306, P.R.China Tel:+86 757 28376123 | Fax:+86 757 28308823 E-mail:export@be-tech.com.cn | www.betech-security.com